

**INTERSECTION: ECR & Encinitas Blvd**

Group Assignment: **NONE**  
 Field Master Assignment: **NONE**  
 System Reference Number: **31**

N/S Street Name: **Not Assigned**  
 E/W Street Name: **Not Assigned**

Last Database Change: 1/15/2019 12:09

Change Record					
Change	By	Date	Change	By	Date

Notes: \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_

**Manual Plan**  
 0 = Automatic  
 1-9 = Plan 1-9  
 14 = Free  
 15 = Flash

**Manual Offset**  
 0 = Automatic  
 1 = Offset A  
 2 = Offset B  
 3 = Offset C

Drop Number	1	<C/0+0+0>
Zone Number	0	<C/0+0+1>
Area Number	0	<C/0+0+2>
Area Address	1	<C/0+0+3>
QuicNet Channel	Unknown	(QuicNet)

Manual Plan		<C/0+A+1>
Manual Offset		<C/0+B+1>

Flash Start	0	<F/1+0+E>
Red Revert	5.0	<F/1+0+F>
All Red Start	5.0	<F/1+C+0>

Exclusive Walk	0	<F/1+0+0>
Exclusive FDW	0	<F/1+0+1>
All Red Clear	0.0	<F/1+0+2>

**Communication Addresses**

**Manual Selection**

**Start / Revert Times**

**Exclusive Ped Phase**

(Outputs specified in Assignable  
 Outputs at E/127+A+E & F)

Row	Phase Names ---->	Phase							
		1	2	3	4	5	6	7	8
0	Ped Walk	0	4	0	4	0	4	0	4
1	Ped FDW	0	20	0	28	0	24	0	31
2	Min Green	4	10	4	10	4	10	4	10
3	Type 3 Disconnect	0	0	0	0	0	0	0	0
4	Added per Vehicle	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0
5	Veh Extension	2.0	3.5	2.0	3.5	2.0	3.5	2.0	3.5
6	Max Gap	4.0	5.0	4.0	5.0	4.0	5.0	5.0	5.0
7	Min Gap	1.0	2.0	1.0	2.0	1.0	2.0	1.0	2.0
8	Max Limit	25	40	29	40	29	40	30	40
9	Max Limit 2	30	70	40	20	30	70	40	30
A	Adv. / Delay Walk	0	0	0	0	0	0	0	0
B	PE Min Ped FDW	0	0	0	0	0	0	0	0
C	Cond Serv Check	0	0	0	0	0	0	0	0
D	Reduce Every	0.5	1.0	0.5	1.0	0.5	1.0	0.5	1.0
E	Yellow Change	3.2	4.3	3.2	4.7	3.2	4.3	3.2	4.7
F	Red Clear	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0

**Phase Timing - Bank 1** <C+0+F=1>

	9	A	B	C	D
Phase 1	0	0	0	0	0.0
Phase 2	20	0	0	0	0.0
Phase 3	0	0	0	0	0.0
Phase 4	20	0	0	0	0.0
Phase 5	0	0	0	0	0.0
Phase 6	20	0	0	0	0.0
Phase 7	0	0	0	0	0.0
Phase 8	20	0	0	0	0.0

Max Initial  
 Alternate Walk  
 Alternate FDW  
 Alternate Initial  
 Alternate Extension

**Alternate Timing** <C+0+F=1>

	E
RR-1 Delay	0
RR-1 Clear	0
EV-A Delay	0
EV-A Clear	1
EV-B Delay	0
EV-B Clear	1
EV-C Delay	0
EV-C Clear	1
EV-D Delay	0
EV-D Clear	1
RR-2 Delay	0
RR-2 Clear	0
View EV Delay	---
View EV Clear	---
View RR Delay	---
View RR Clear	---

**Preempt Timing**

	F	Row
Permit	12345678	0
Red Lock	_____	1
Yellow Lock	_____	2
Min Recall	2 6	3
Ped Recall	_____	4
View Set Peds	-----	5
Rest In Walk	_____	6
Red Rest	_____	7
Dual Entry	_____	8
Max Recall	_____	9
Soft Recall	_____	A
Max 2	_____	B
Cond. Service	_____	C
Man Cntrl Calls	_____	D
Yellow Start	2 6	E
First Phases	4 8	F

**Phase Functions** <C+0+F=1>

		Overlap							
Column Numbers ---->		1	2	3	4	5	6	7	8
Row	Overlap Name ---->								
0	Load Switch Number	0	0	0	0	0	0	0	0
1	Veh Set 1 - Phases								
2	Veh Set 2 - Phases								
3	Veh Set 3 - Phases								
4	Neg Veh Phases								
5	Neg Ped Phases								
6	Green Omit Phases								
7	Green Clear Omit Phs.								
8									
9									
A									
B									
C									
D	Green Clear	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0
E	Yellow Change	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0
F	Red Clear	0.0	0.0	0.0	0.0	0.0	0.0	0.0	0.0

Overlap Assignments <C+0+E=29>

- Extra 1 Flags**  
 1 = TBC Type 1  
 2 = NEMA Ext. Coord  
 3 = Auto Daylight Savings  
 4 = Solid FDW on EV  
 5 = Extended Status  
 6 = International Ped  
 7 = Flash - Clear Outputs  
 8 = Split Ring

- Extra 2 Flags**  
 1 = AWB During Initial  
 2 = LMU Installed  
 3 = Disable Min Walk  
 4 = QuicNet/4 System  
 5 = Ignore P/P on EV  
 6 =  
 7 = Allow QuicNet PE  
 8 =

	C	Row
EV-A	0	0
EV-B	0	1
EV-C	0	2
EV-D	0	3
RR-1 *	---	4
RR-2 *	---	5
SE-1	0	6
SE-2	0	7

**Preempt Priority**  
 <C+0+E=125>  
 (\* RR-1 is always Highest, and RR-2 is always Second Highest)

Row	Column Numbers ---->	E
0	Exclusive Phases	
1	RR-1 Clear Phases	
2	RR-2 Clear Phases	
3	RR-2 Limited Service	
4	Prot / Perm Phases	
5	Flash to PE Circuits	
6	Flash Entry Phases	
7	Disable Yellow Range	
8	Disable Ovp Yel Range	
9	Overlap Yellow Flash	
A	EV-A Phases	2 5
B	EV-B Phases	4 7
C	EV-C Phases	1 6
D	EV-D Phases	3 8
E	Extra 1 Config. Bits	1 3 5
F	IC Select (Interconnect)	2

Configuration <C+0+E=125>

	F
Ext. Permit 1 Phases	
Ext. Permit 2 Phases	
Exclusive Ped Assign	
Preempt Non-Lock	12345678
Ped for 2P Output	2
Ped for 6P Output	6
Ped for 4P Output	4
Ped for 8P Output	8
Yellow Flash Phases	
Low Priority A Phases	
Low Priority B Phases	
Low Priority C Phases	
Low Priority D Phases	
Restricted Phases	
Extra 2 Config. Bits	4 7

Configuration <C+0+E=125>

	F
Fast Green Flash Phase	
Green Flash Phases	
Flashing Walk Phases	
Guaranteed Passage	
Simultaneous Gap Term	12345678
Sequential Timing	
Advance Walk Phases	
Delay Walk Phases	
External Recall	
Start-up Overlap Green	
Max Extension	
Inhibit Ped Reservice	
Semi-Actuated	
Start-up Overlap Yellow	
Start-up Vehicle Calls	12345678
Start-up Ped Calls	12345678

Specials <C+0+F=2>

- Flash to PE & PE Non-Lock**  
 1 = EV A 5 = RR 1  
 2 = EV B 6 = RR 2  
 3 = EV C 7 = SE 1  
 4 = EV D 8 = SE 2

- IC Select Flags**  
 1 =  
 2 = Modem  
 3 = 7-Wire Slave  
 4 = Flash / Free  
 5 =  
 6 = Simplex Master  
 7 = 7-Wire Master  
 8 = Offset Interrupter

	2	Row
Phase 1	20	1
Phase 2	40	2
Phase 3	20	3
Phase 4	40	4
Phase 5	20	5
Phase 6	40	6
Phase 7	20	7
Phase 8	40	8

**Coordination Transition Minimums**  
 <C+0+C=5>

Column Numbers ---->		Plan								
Plan Name ---->		1	2	3	4	5	6	7	8	9
0	Cycle Length	135	130	140	140	100	120	100	100	135
1	Phase 1 - ForceOff	31	28	32	31	55	90	55	55	31
2	Phase 2 - ForceOff	0	0	0	0	0	0	0	0	0
3	Phase 3 - ForceOff	60	90	108	97	20	30	20	20	98
4	Phase 4 - ForceOff	98	63	82	67	40	64	40	40	61
5	Phase 5 - ForceOff	124	115	129	123	55	90	55	55	124
6	Phase 6 - ForceOff	0	0	0	0	0	0	0	0	0
7	Phase 7 - ForceOff	98	56	69	60	20	30	20	20	60
8	Phase 8 - ForceOff	61	90	103	97	40	64	40	40	98
9	Ring Offset	0	0	0	0	0	0	0	0	0
A	Offset 1	113	15	139	128	0	117	0	0	113
B	Offset 2	0	0	0	0	0	0	0	0	0
C	Offset 3	0	0	0	0	0	0	0	0	0
D	Perm 1 - End	34	31	37	35	15	12	15	15	34
E	Hold Release	255	130	255	255	255	120	255	255	255
F	Zone Offset	0	0	0	0	0	0	0	0	0

Coordination - Bank 1 <C+0+C=1>

0	Ped Adjustment	3	5	0	0	0	0	0	0	3
1	Perm 2 - Start	0	0	0	0	0	0	0	0	0
2	Perm 2 - End	0	0	0	0	0	0	0	0	0
3	Perm 3 - Start	0	0	0	0	0	0	0	0	0
4	Perm 3 - End	0	0	0	0	0	0	0	0	0
5	Reservice Time	0	0	0	0	0	0	0	0	0
6	Reservice Phases									
7										
8	Pretimed Phases									
9	Max Recall									
A	Perm 1 Veh Phase	12345678	12345678	12345678	12345678	12345678	12345678	12345678	12345678	12345678
B	Perm 1 Ped Phase	2 4 6 8	2 4 6 8	12345678	12345678	12345678	12345678	12345678	12345678	12345678
C	Perm 2 Veh Phase									
D	Perm 2 Ped Phase									
E	Perm 3 Veh Phase									
F	Perm 3 Ped Phase									

Coordination - Bank 2 <C+0+C=2>

Coord Extra  
 1 = Programmed WALK Time for Sync Phases  
 2 = Always Terminate Sync Phase Peds

Row	E	Row	
0		0	
1	Plan 1 - Sync	2 6	1
2	Plan 2 - Sync	2 6	2
3	Plan 3 - Sync	2 6	3
4	Plan 4 - Sync	2 6	4
5	Plan 5 - Sync	2 6	5
6	Plan 6 - Sync	2 6	6
7	Plan 7 - Sync	2 6	7
8	Plan 8 - Sync	2 6	8
9	Plan 9 - Sync	2 6	9
A	NEMA Sync		A
B	NEMA Hold		B
C			C
D			D
E	Coord Extra		E
F			F

Sync Phases <C+0+C=1>

Row	F	Row	
0	Free Lag	2 4 6 8	0
1	Plan 1 - Lag	1 4 6 7	1
2	Plan 2 - Lag	1 3 6 8	2
3	Plan 3 - Lag	1 3 6 8	3
4	Plan 4 - Lag	1 3 6 8	4
5	Plan 5 - Lag	2 4 6 8	5
6	Plan 6 - Lag	2 4 6 8	6
7	Plan 7 - Lag	2 4 6 8	7
8	Plan 8 - Lag	2 4 6 8	8
9	Plan 9 - Lag	1 3 6 8	9
A	External Lag		A
B			B
C			C
D			D
E			E
F			F

Lag Phases <C+0+C=1>

Row	Column 9		Column A		Column B		Column C		Column D		Column E		Column F		Row
0	Spec. Funct. 1	0	NOT-3	0	Max 2	0	Pretimed	0	Set Monday	0	Dial 2 (7-Wire)	0	Sim Term	0	0
1	Spec. Funct. 2	0	NOT-4	0	System Det 1	39	Plan 1	0	Ext. Perm 1	0	Dial 3 (7-Wire)	0	EV-A	71	1
2	Spec. Funct. 3	0	OR-4 (a)	0	System Det 2	40	Plan 2	0	Ext. Perm 2	0	Offset 1 (7-Wire)	0	EV-B	72	2
3	Spec. Funct. 4	0	OR-4 (b)	0	System Det 3	41	Plan 3	0	Reserved	0	Offset 2 (7-Wire)	0	EV-C	73	3
4	NAND-3 (a)	0	OR-5 (a)	0	System Det 4	45	Plan 4	0	Set Clock	0	Offset 3 (7-Wire)	0	EV-D	74	4
5	NAND-3 (b)	0	OR-5 (b)	0	System Det 5	43	Plan 5	0	Stop Time	82	Free (7-Wire)	0	RR-1	51	5
6	NAND-4 (a)	0	OR-6 (a)	0	System Det 6	44	Plan 6	0	Flash Sense	81	Flash (7-Wire)	0	RR-2	52	6
7	NAND-4 (b)	0	OR-6 (b)	0	System Det 7	63	Plan 7	0	Manual Enable	0	Excl. Ped Omit	0	Spec. Event 1	0	7
8	OR-7 (a)	0	Fig 3 Diamond	0	System Det 8	64	Plan 8	0	Man. Advance	0	NOT-1	0	Spec. Event 2	0	8
9	OR-7 (b)	0	Fig 4 Diamond	0	Max Inhibit (nema)	0	Plan 9	0	External Alarm	75	NOT-2	0	External Lag	0	9
A	OR-7 (c)	0	AND-4 (a)	0	Force A (nema)	0	DELAY-A	0	Phase Bank 2	0	OR-1 (a)	0	AND-1 (a)	0	A
B	OR-7 (d)	0	AND-4 (b)	0	Force B (nema)	0	DELAY-B	0	Phase Bank 3	0	OR-1 (b)	0	AND-1 (b)	0	B
C	OR-8 (a)	0	NAND-1 (a)	0	C.N.A. (nema)	0	DELAY-C	0	Overlap Set 2	0	OR-2 (a)	0	AND-2 (a)	0	C
D	OR-8 (b)	0	NAND-1 (b)	0	Hold (nema)	0	DELAY-D	0	Overlap Set 3	0	OR-2 (b)	0	AND-2 (b)	0	D
E	OR-8 (c)	0	NAND-2 (a)	0	Max Recall	0	DELAY-E	0	Detector Set 2	200	OR-3 (a)	0	AND-3 (a)	0	E
F	OR-8 (d)	0	NAND-2 (b)	0	Min Recall	0	DELAY-F	0	Detector Set 3	0	OR-3 (b)	0	AND-3 (b)	0	F

Assignable Inputs

<C+0+E=126>

Row	Column 9		Column A		Column B		Column C		Column D		Column E		Column F		Row
0	Phase ON - 1	0	Preempt Fail	0	Flasher 0	0	Free	0	NOT-1	0	TOD Out 1	200	Dial 2 (7-Wire)	0	0
1	Phase ON - 2	0	Sp Evnt Out 1	0	Flasher 1	0	Plan 1	0	OR-1	0	TOD Out 2	0	Dial 3 (7-Wire)	0	1
2	Phase ON - 3	0	Sp Evnt Out 2	0	Fast Flasher	0	Plan 2	0	OR-2	0	TOD Out 3	0	Offset 1 (7-Wire)	0	2
3	Phase ON - 4	0	Sp Evnt Out 3	0	Fig 3 Diamond	0	Plan 3	0	OR-3	0	TOD Out 4	0	Offset 2 (7-Wire)	0	3
4	Phase ON - 5	0	Sp Evnt Out 4	0	Fig 4 Diamond	0	Plan 4	0	AND-1	0	TOD Out 5	0	Offset 3 (7-Wire)	0	4
5	Phase ON - 6	0	Sp Evnt Out 5	0			Plan 5	0	AND-2	0	TOD Out 6	0	Free (7-Wire)	0	5
6	Phase ON - 7	0	Sp Evnt Out 6	0			Plan 6	0	AND-3	0	TOD Out 7	0	Flash (7-Wire)	0	6
7	Phase ON - 8	0	Sp Evnt Out 7	0			Plan 7	0	NOT-2	0	TOD Out 8	0	Preempt	0	7
8	Ph. Check - 1	0	Sp Evnt Out 8	0	NOT-3	0	Plan 8	0	EV-A	0	Adv. Warn - 1	0	Low Priority A	0	8
9	Ph. Check - 2	0			NOT-4	0	Plan 9	0	EV-B	0	Adv. Warn - 2	0	Low Priority B	0	9
A	Ph. Check - 3	0	Detector Fail	0	OR-4	0	Spec. Funct. 3	0	EV-C	0	DELAY-A	0	Low Priority C	0	A
B	Ph. Check - 4	0	Spec. Funct. 1	0	OR-5	0	Spec. Funct. 4	0	EV-D	0	DELAY-B	0	Low Priority D	0	B
C	Ph. Check - 5	0	Spec. Funct. 2	0	OR-6	0	NAND-3	0	RR-1	0	DELAY-C	0			C
D	Ph. Check - 6	0	Central Control	0	AND-4	0	NAND-4	0	RR-2	0	DELAY-D	0			D
E	Ph. Check - 7	0	Excl. Ped DW	0	NAND-1	0	OR-7	0	Spec. Event 1	0	DELAY-E	0			E
F	Ph. Check - 8	0	Excl. Ped WK	0	NAND-2	0	OR-8	0	Spec. Event 2	0	DELAY-F	0			F

Assignable Outputs

<C+0+E=127>

Row	Phase Names ---->	Phase							
		1	2	3	4	5	6	7	8
0	Ped Walk	0	7	0	7	0	7	0	7
1	Ped FDW	0	15	0	15	0	15	0	15
2	Min Green	4	7	4	4	4	7	4	4
3	Type 3 Disconnect	0	20	0	20	0	20	0	20
4	Added per Vehicle	0.0	2.0	0.0	2.0	0.0	2.0	0.0	2.0
5	Veh Extension	2.0	4.0	2.0	2.5	2.0	4.0	2.0	2.5
6	Max Gap	3.0	6.0	3.0	3.0	3.0	6.0	3.0	3.0
7	Min Gap	0.5	2.0	0.5	1.5	0.5	2.0	0.5	1.5
8	Max Limit	20	30	20	25	20	30	20	25
9	Max Limit 2	30	50	30	40	30	50	30	40
A	Adv. / Delay Walk	0	0	0	0	0	0	0	0
B	PE Min Ped FDW	7	7	7	7	7	7	7	7
C	Cond Serv Check	10	10	10	10	10	10	10	10
D	Reduce Every	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
E	Yellow Change	3.0	4.0	3.0	3.0	3.0	4.0	3.0	3.0
F	Red Clear	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0

Phase Timing - Bank 2 <C+0+F=2>

	9	A	B	C	D
Phase 1	0	0	0	0	0.0
Phase 2	20	0	0	0	0.0
Phase 3	0	0	0	0	0.0
Phase 4	20	0	0	0	0.0
Phase 5	0	0	0	0	0.0
Phase 6	20	0	0	0	0.0
Phase 7	0	0	0	0	0.0
Phase 8	20	0	0	0	0.0

Max Initial  
Alternate Walk  
Alternate FDW  
Alternate Initial  
Alternate Extension

Alternate Timing

Transition Type  
0.X = Shortway  
1.X = Lengthen  
X.1 thru X.4 =  
Number of  
cycles when  
lengthing

Transition Type	0.4	<C/5+1+9>
-----------------	-----	-----------

**TBC Transition**

Lag Hold Phases		<C/5+1+A>
-----------------	--	-----------

**Coordinated Lag Hold Phases**

Daylight Savings  
Date  
If set to all zeros,  
standard dates  
will be used.

Begin Month	3	<C/5+2+A>
Begin Week	2	<C/5+2+B>
End Month	11	<C/5+2+C>
End Week	1	<C/5+2+D>

**Daylight Savings Time**

Row	Phase Names ---->	Phase							
		1	2	3	4	5	6	7	8
0	Ped Walk	0	7	0	7	0	7	0	7
1	Ped FDW	0	15	0	15	0	15	0	15
2	Min Green	4	7	4	4	4	7	4	4
3	Type 3 Disconnect	0	20	0	20	0	20	0	20
4	Added per Vehicle	0.0	2.0	0.0	2.0	0.0	2.0	0.0	2.0
5	Veh Extension	2.0	4.0	2.0	2.5	2.0	4.0	2.0	2.5
6	Max Gap	3.0	6.0	3.0	3.0	3.0	6.0	3.0	3.0
7	Min Gap	0.5	2.0	0.5	1.5	0.5	2.0	0.5	1.5
8	Max Limit	20	30	20	25	20	30	20	25
9	Max Limit 2	30	50	30	40	30	50	30	40
A	Adv. / Delay Walk	0	0	0	0	0	0	0	0
B	PE Min Ped FDW	7	7	7	7	7	7	7	7
C	Cond Serv Check	10	10	10	10	10	10	10	10
D	Reduce Every	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0
E	Yellow Change	3.0	4.0	3.0	3.0	3.0	4.0	3.0	3.0
F	Red Clear	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0

Phase Timing - Bank 3 <C+0+F=3>

	9	A	B	C	D
Phase 1	0	0	0	0	0.0
Phase 2	20	0	0	0	0.0
Phase 3	0	0	0	0	0.0
Phase 4	20	0	0	0	0.0
Phase 5	0	0	0	0	0.0
Phase 6	20	0	0	0	0.0
Phase 7	0	0	0	0	0.0
Phase 8	20	0	0	0	0.0

Max Initial  
Alternate Walk  
Alternate FDW  
Alternate Initial  
Alternate Extension

Alternate Timing

Time B4 Yellow	0.0	<F/1+C+E>
Phase Number	0	<F/1+C+F>

**Advance Warning Beacon - Sign 1**

Time B4 Yellow	0.0	<F/1+D+E>
Phase Number	0	<F/1+D+F>

**Advance Warning Beacon - Sign 2**

Column Numbers ---->		0	1	2	3	1	3
Row	Detector Name	C1 Pin Number	Attributes	Phase(s)	Assign	Delay	Carry-over
0		39	45 7	2	123 8	0.0	0.0
1		40	45 7	6	1 8	0.0	0.0
2		41	45 7	4	123 8	0.0	0.0
3		42	45 7	8	123 8	0.0	0.0
4		43	45 7	2	123 8	0.0	0.0
5		44	45 7	6	123 8	0.0	0.0
6		45	45 7	4	123 8	0.0	0.0
7		46	45 7	8	123 8	0.0	0.0
8		47	67	2	123 8	0.0	0.0
9		48	67	6	123	0.0	0.0
A		49	67	4	123	0.0	0.0
B		50	67	8	123	0.0	0.0
C		55	45 7	5	123 8	0.0	0.0
D		56	45 7	1	123 8	0.0	0.0
E		57	45 7	7	123 8	0.0	0.0
F		58	45 7	3	123 8	0.0	0.0

Column Numbers ---->		Ped / Phase / Overlap								Row
		1	2	3	4	5	6	7	8	
Walk		0	0	0	0	0	0	0	0	0
Don't Walk		0	0	0	0	0	0	0	0	1
Phase Green		0	0	0	0	0	0	0	0	2
Phase Yellow		0	0	0	0	0	0	0	0	3
Phase Red		0	0	0	0	0	0	0	0	4
Overlap Green		0	0	0	0	0	0	0	0	5
Overlap Yellow		0	0	0	0	0	0	0	0	6
Overlap Red		0	0	0	0	0	0	0	0	7

Redirect Phase Outputs <C+0+E=127>

Cabinet Type | 0 <E/125+D+0>

**Enable Redirection**  
(Enable Redirection = 30)

Max OFF (minutes) | 254 <D/0+0+1>

Max ON (minutes) | 15 <D/0+0+2>

**Detector Failure Monitor**

Column Numbers ---->		4	5	6	7	2	4
Row	Detector Name	C1 Pin Number	Attributes	Phase(s)	Assign	Delay	Carry-over
0		59	45 7	5	123	0.0	0.0
1		40	45 7	1 6	2 8	0.0	0.0
2		61	45 7	7	123	0.0	0.0
3		62	45 7	3	123	0.0	0.0
4		63	45 7	2	123 8	0.0	0.0
5		64	45 7	6	123	0.0	0.0
6		65	45 7	4	123 8	0.0	0.0
7		66	45 7	8	123 8	0.0	0.0
8		67	2	2	123	0.0	0.0
9		68	2	6	123 8	0.0	0.0
A		69	2	4	123 8	0.0	0.0
B		70	2	8	123 8	0.0	0.0
C		76	45 7	2	123 8	0.0	0.0
D		77	45 7	6	123	0.0	0.0
E		78	45 7	4	123	0.0	0.0
F		79	45 7	8	123 8	0.0	0.0

**Detector Attributes**

- 1 = Full Time Delay
- 2 = Ped Call
- 3 =
- 4 = Count
- 5 = Extension
- 6 = Type 3
- 7 = Calling
- 8 = Alternate

**Det. Assignments**

- 1 = Det. Set 1
- 2 = Det. Set 2
- 3 = Det. Set 3
- 4 =
- 5 =
- 6 = Failure - Min Recall
- 7 = Failure - Max Recall
- 8 = Report on Failure

Detector Assignments <C+0+E=126>

<C+0+D=0>

**Disable Alarms**

- 1 = Stop Time
- 2 = Flash Sense
- 3 = Keyboard Entry
- 4 = Manual Plan
- 5 = Police Control
- 6 = External Alarm
- 7 = Detector Failure
- 8 =

	B	Row
DELAY-A	0	A
DELAY-B	0	B
DELAY-C	0	C
DELAY-D	0	D
DELAY-E	0	E
DELAY-F	0	F

**Delay Logic Times**  
<C+0+D=0> (seconds)

Omit Alarm | <C/5+F+0>

**Disable Alarm Reporting**

Row	Time	Plan	Offset	Day of Week
0	00 : 00	E	A	1234567
1	06 : 30	2	A	23456
2	07 : 15	4	A	23456
3	09 : 00	2	A	23456
4	11 : 00	1	A	1234567
5	15 : 42	3	A	23456
6	18 : 00	1	A	23456
7	19 : 00	E	A	1234567
8	08 : 00	2	A	1 7
9	00 : 00	0	0	
A	00 : 00	0	0	
B	00 : 00	0	0	
C	00 : 00	0	0	
D	00 : 00	0	0	
E	00 : 00	0	0	
F	00 : 00	0	0	

**TOD Coordination** <C+0+9=0.1>  
(Bank 1)

Time	Funct.	Day of Week
00 : 00	E	1234567
08 : 30	E	1234567
20 : 00	E	1234567
07 : 20	F	23456
08 : 40	F	23456
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	

**TOD Function** <C+0+7=0.1>

Column 4	Phases/Bits
	4 78
	78
	4 78
	1

<C+0+E=27>

Day	Year	Month	Holiday Type
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	

**Holiday Dates** <C+0+8=1.1>  
(Bank 1)

Time	Plan	Offset	Holiday Type
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	

**Holiday Events** <C+0+9=1.1>  
(Bank 1)

- T.O.D. Functions**
- 0 =
  - 1 = Red Lock
  - 2 = Yellow Lock
  - 3 = Veh Min Recall
  - 4 = Ped Recall
  - 5 =
  - 6 = Rest In Walk
  - 7 = Red Rest
  - 8 = Double Entry
  - 9 = Veh Max Recall
  - A = Veh Soft Recall
  - B = Maximum 2
  - C = Conditional Service
  - D = Free Lag Phases
  - E = Bit 1 - Local Override
  - Bit 4 - Disable Detector OFF Monitor
  - Bit 5 - Disable Low Priority Preempt
  - Bit 7 - Detector Count Monitor
  - Bit 8 - Real Time Split Monitor
  - F = Output Bits 1 thru 8

Row	Time	Plan	Offset	Day of Week
0	00 : 00	0	0	
1	00 : 00	0	0	
2	00 : 00	0	0	
3	00 : 00	0	0	
4	00 : 00	0	0	
5	00 : 00	0	0	
6	00 : 00	0	0	
7	00 : 00	0	0	
8	00 : 00	0	0	
9	00 : 00	0	0	
A	00 : 00	0	0	
B	00 : 00	0	0	
C	00 : 00	0	0	
D	00 : 00	0	0	
E	00 : 00	0	0	
F	00 : 00	0	0	

**TOD Coordination** <C+0+9=0.2>  
(Bank 2)

Time	Funct.	Holiday Type
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	
00 : 00	0	

**Holiday TOD Function** <C+0+7=0.2>

Column 4	Phases/Bits

<C+0+E=28>

Day	Year	Month	Holiday Type
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	
00	00	0	

**Holiday Dates** <C+0+8=1.2>  
(Bank 2)

Time	Plan	Offset	Holiday Type
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	
00 : 00	0	0	

**Holiday Events** <C+0+9=1.2>  
(Bank 2)

- Plan Select**
- 1 thru 9 = Coordination Plan 1 thru 9
  - 14 or E = Free
  - 15 or F = Flash
- Offset Select**
- A = Offset A
  - B = Offset B
  - C = Offset C
- Month Select**
- 1 = January
  - 2 = February
  - 3 = March
  - 4 = April
  - 5 = May
  - 6 = June
  - 7 = July
  - 8 = August
  - 9 = September
  - A = October
  - B = November
  - C = December

Row	6 Clear	7 Time	8 Ped Call	9 Hold	A Advance	B Force Off	C Vehicle Call	D Permit Phases	E Ped Omit	F Output
0		0								
1		0								
2		0								
3		0								
4		0								
5		0								
6		0								
7		0								
8		0								
9		0								
A		0								
B		0								
C		0								
D		0								
E		0								
F		0								

Special Event Schedule -- Table 1

<C+0+E=27>

Notes: \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_

0 <E/27+5+F>  
**Limited Service Interval**

Row	6 Clear	7 Time	8 Ped Call	9 Hold	A Advance	B Force Off	C Vehicle Call	D Permit Phases	E Ped Omit	F Output
0		0								
1		0								
2		0								
3		0								
4		0								
5		0								
6		0								
7		0								
8		0								
9		0								
A		0								
B		0								
C		0								
D		0								
E		0								
F		0								

Special Event Schedule -- Table 2

<C+0+E=28>

Notes: \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_

0 <E/28+5+F>  
**Limited Service Interval**



Min Time (seconds) | 0 | <F/1+0+8>  
**Min Green Before PE Force Off**

Max Time (minutes) | 255 | <F/1+0+9>  
**Max Preempt Time Before Failure**

Min Time (seconds) | 0 | <F/1+0+A>  
**Min Time Between Same Preempts**  
 (Does Not Apply To Railroad Preempt)

Low Pri. Channel | | <E/125+C+8>  
**Disable Low Priority Channel**

- Low Priority  
 1 = Channel A  
 2 = Channel B  
 3 = Channel C  
 4 = Channel D

Delay Time (seconds) | 0 | <F/1+A+D>  
**Bus Delay**

Max Time (seconds) | 0 | <F/1+A+E>  
**Max Early Green**

Max Time (seconds) | 0 | <F/1+A+F>  
**Max Green Extension**

Row	Time	Headway	Direction	Day of Week
0	00 : 00	0	0	_____
1	00 : 00	0	0	_____
2	00 : 00	0	0	_____
3	00 : 00	0	0	_____
4	00 : 00	0	0	_____
5	00 : 00	0	0	_____
6	00 : 00	0	0	_____
7	00 : 00	0	0	_____
8	00 : 00	0	0	_____
9	00 : 00	0	0	_____
A	00 : 00	0	0	_____
B	00 : 00	0	0	_____
C	00 : 00	0	0	_____
D	00 : 00	0	0	_____
E	00 : 00	0	0	_____
F	00 : 00	0	0	_____

Headway Time  
 (minutes)  
 1 thru 9 = 1 thru 9  
 A = 10  
 B = 11  
 C = 12  
 D = 13  
 E = 14  
 F = 15

Headway <C+0+9=2.1>

**Low Priority Preemption (Bus Priority)**

Only available with *Program 233RV2.B* (and above)

Note: Also see "Time of Day Functions", Function E, Bit 5 (Disable Low Priority)